

MONTÁŽNÍ NÁVOD PRO SVÍTIDLA TYPU RAMBO - LED

Svítidla RAMBO-LED jsou svítidla vybavená LED zdroji, určená pro osvětlování interiérů, ve kterých je nutností použít nerozbitná a nerozebíratelná svítidla, jako jsou např. věžeňské cely, chodby, podchody apod.


Postup montáže svítidla RAMBO

1. Vyndejte svítidlo z transportního obalu.
2. Uvolněte zapuštěné šrouby v čítku a čílka vysuňte z tělesa.
3. Protáhněte napájecí kabel skrz pryžovou průchodku v tělese.
4. Pomocí čtyř vrutů a hmoždinek připevněte svítidlo na strop (stěnu) osvětlovaného prostoru.
5. V případě montáže varianty IP67 uvolněte dva imbusové šrouby na ucpávce svítidla a protáhněte napájecí kabel skrz ucpávkovou vývodku IP67. Řádně ji dotáhněte. Přívodní kabel do svítidla musí mít vnější průměr v rozmezí 7,5 až 12 mm, což je nutná podmínka pro řádnou funkci ucpávkové vývodky.
6. Sejměte krycí profil nad svorkovnicí a rozpojte přívodní svorkovnicí.
7. Zapojte napájecí kabel do volné části přívodní svorkovnice následovně:

Verze 12V/DC

na svorku + kladný pól
 na svorku - záporný pól

Verze 230V/ 50Hz

na svorku L1 - fázový vodič
 na svorku N - nulový vodič
 na svorku  - ochranný vodič

Přívodní svorkovnice je určena pro připojení vodičů s průřezem 0,75 - 2,5 mm².

- Dbejte na správné odizolování (8 – 9 mm) a zasunutí vodiče do svorkovnice.
8. Spojte přívodní svorkovnicí a zajistěte ji proti samovolnému rozpojení.
 9. Nasuňte zpět krycí hliníkový profil nad svorkovnicí.
 10. V případě montáže varianty IP67 nasuňte těsnící zátku svítidla do trubky. Dbejte na správné zasunutí reflektoru do západek na těsnící zátku. Utáhněte imbusové šrouby na ucpávce svítidla utahovacím momentem 3 až 4 Nm.
 11. Po dotažení šroubů ucpávky zkontrolujte, jestli gumový o-kroužek rovnoměrně doléhá na vnitřní stranu PC trubky.
 12. Zasuňte čílka do zámků v tělese a připevněte je pomocí 4 šroubů.

Upozornění pro montáž svítidel RAMBO

Svítidlo smí na elektrickou síť připojovat pouze osoba s odpovídající kvalifikací dle platné vyhlášky o odborné způsobilosti v elektrotechnice.

Výrobce je zařazen do systému zpětného odběru a recyklace obalů firmy EKO-KOM. (EK-F06022453)

Při nedodržení montážního návodu výrobce neručí za případné vzniklé škody!

Údržba:

Konstrukce svítidla nevyžaduje zvláštní údržbu. Znečištěné těleso omyjeme vlažnou vodou s přidavkem saponátového čistícího prostředku.



MOUNTING INSTRUCTION FOR SERIES RAMBO - LED

Series RAMBO-LED are designed for premises with high risk of damage.


Mounting

1. Take the fixture from transporting packing.
2. Unbolt 4 screws and remove the plastic end-caps from the fixture.
3. Lead supply cable through rubber gland in the housing.
4. Install the fixture on the ceiling (wall) by means of four bolts and plugs.
5. In case of variant IP67 unbolt two hexagonal screws on the plug of the fixture and lead supply cable through sealing gland IP67. Tight it properly. Outside diameter of supply cable must be 7,5 -12 mm.
6. Remove covering profile over terminal block and disconnect feeding terminal block.
7. Connect supply cable to free part of feeding terminal block as followed :

Verzion 12V/DC

on connector + positive pole
 on connector - negative pole

Verzion 230V/ 50Hz

on connector L1 – phase conductor
 on connector N - neutral conductor
 on connector  - protective conductor

Feeding terminal block is used for connection of conductors in cut 0,75-2,5mm². Attend to correct stripping (8 – 9 mm) and connection to terminal block.

8. Connect feeding terminal block and fix against of self-disconnection.
9. Put the covering profile back over terminal block
10. In case of variant IP67 equip with sealing plug into the tube. Attend to correct insertion of reflector in the tube. Tighten hexagonal screws on the plug with torque 3-4 Nm.
11. After screws tightened on the plug it is necessary to check if rubber O-ring seal properly inside of the tube.
12. Equip with plastic end-caps and fix by means of four screws.

Warning for mounting series RAMBO

The fixtures can be installed by authorised persons only according to valid regulations. Producer is included in recycling system provided by EKO-KOM company (EK-F06022453) Producer does not take the responsibility for eventual damage in case of mounting instruction default!

Maintenance :

Construction of the lighting fixtures does not need any special maintainance. Clean polluted housing by tepid water with added detergent .

